

# ORIGINAL - PLASTIC MF BASE -

Original spare part



## The cost-effective original spare parts

Discover our ORIGINAL signal lamps for printed circuit boards. These lamps with OSRAM's reliable OEM quality feature a wide product range and can be used for instrument and switch lighting.

# Product datasheet

## Technical data

### Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

### General Product Information

Global order reference	2352MFX6
------------------------	----------


### Electrical Data

Power input	2.13 W
Nominal voltage	12.0 V
Nominal wattage	2 W
Test voltage	13.5 V
Power input tolerance	±10 %

### Photometric Data

Nominal luminous flux	11.8 lm
Luminous flux tolerance	±20 %

### Physical Attributes & Dimensions



Diameter	5 mm
Product weight	0.74 g
Length	17.5 mm
Lamp base	BX8.4d-12.5

### Colors & materials

Base color	Pale green
------------	------------

### Lifetime Data

## Product datasheet

Lifespan B3	1500 hr
Lifespan Tc	6000 hr

### Capabilities

Thickness of PCB	1.25 mm
Technology	AUX

### Certificates & standards

ECE category	-
Approval marks – approval	-

### Environmental & Regulatory Information


Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Primary article identifier	4008321097149   4008321011039   4062172046947
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	No declarable substances contained

### Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4062172046947	ORIGINAL - PLASTIC MF BASE 2352MFX6	Unpacked 1	17 mm x 5 mm x 5 mm		1.00 g
4062172046961	ORIGINAL - PLASTIC MF BASE 2352MFX6	Shipping carton box 50	148 mm x 115 mm x 55 mm	0.94 dm <sup>3</sup>	122.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

### Download Data

File
 User instruction GPRS_Safety symbols instructions

#### Application advice

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

## Product datasheet

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



# OSRAM